

Blue LED Pulsed Light Source

LS-475



Installation and Operation Manual

Document Number 000-10000-100-02-1005

Offices: **Ocean Optics, Inc.**
830 Douglas Ave., Dunedin, FL, USA 34698
Phone 727.733.2447
Fax 727.733.3962
8 a.m.– 8 p.m. (Mon-Thu), 8 a.m.– 6 p.m. (Fri) EST

Ocean Optics B.V. (Europe)
Geograaf 24, 6921 EW DUIVEN, The Netherlands
Phone 31-(0)26-3190500
Fax 31-(0)26-3190505

E-mail: Info@OceanOptics.com (General sales inquiries)
Info@OceanOpticsBV.com (European sales inquiries)
Orders@OceanOptics.com (Questions about orders)
TechSupport@OceanOptics.com (Technical support)



Ocean Optics offers the most comprehensive, innovative and high-quality line of modular spectroscopy tools in the world. Mikropack, a leading supplier of spectroscopy and thin film components, is an essential and valuable partner in this enterprise. We have partnered with Mikropack because they are committed to the same goals of innovation and quality that inspire us here at Ocean Optics. As always, Ocean Optics conducts its business in an open, honest and technically available fashion. We invite you to contact us at Ocean Optics, Inc. (see front cover for contact information) or Mikropack GmbH with any technical questions, comments, or applications inquiries. Mikropack GmbH can be contacted at the following location:

MIKROPACK GmbH
Maybachstraße 11
D-73760 Ostfildern
Germany
Tel.: +49 (0)711 34 16 96-0 • Fax.: +49 (0)711 34 16 96-85
e-mail: info@mikropack.de
internet: www.mikropack.de

Copyright © 2001-2005 Ocean Optics, Inc.

All rights reserved. No part of this publication may be reproduced, stored in a retrieval system, or transmitted, by any means, electronic, mechanical, photocopying, recording, or otherwise, without written permission from Ocean Optics, Inc.

This manual is sold as part of an order and subject to the condition that it shall not, by way of trade or otherwise, be lent, re-sold, hired out or otherwise circulated without the prior consent of Ocean Optics, Inc. in any form of binding or cover other than that in which it is published.

Trademarks

Microsoft, Windows, Windows 95, Windows 98, Windows Me, Windows NT, Windows 2000, Windows XP and Excel are either registered trademarks or trademarks of Microsoft Corporation.

Limit of Liability

Every effort has been made to make this manual as complete and as accurate as possible, but no warranty or fitness is implied. The information provided is on an “as is” basis. Ocean Optics, Inc. shall have neither liability nor responsibility to any person or entity with respect to any loss or damages arising from the information contained in this manual.

Important Safety Notices

1. Do not remove or modify any installed safety device on this equipment. Doing so will void your warranty and create an unsafe operating environment.
2. Dangerous voltages are present in this device. There are NO user serviceable parts inside.
3. Only allow qualified personnel to service this unit.
4. Do not use the unit if it is damaged in any way. Contact your dealer for repair or replacement information.

Table of Contents

About This Manual	iii
Document Purpose and Intended Audience	iii
What's New in this Document.....	iii
Document Summary	iii
Product-Related Documentation.....	iii
Upgrades	iv
Chapter 1: Setup.....	1
Overview.....	1
Unpacking the LS-475.....	2
Contents	2
General Configuration	2
Chapter 2: LS-475 Specifications	3
Operating Environment.....	3
LS-475 Components	3
Front Panel	4
Rear Panel.....	4
Pinout Information	5
Pinout Diagram	6
Chapter 3: Operating Instructions	7
Overview.....	7
Using the Continuous Mode	7
Using the Pulsed Mode	7
Enabling Pulse Mode on an S2000 Spectrometer.....	8
Index.....	11

About This Manual

Document Purpose and Intended Audience

This document provides you with an installation section to get your system up and running.

What's New in this Document

This version of the *Blue LED Pulsed Light Source LS-475 Installation and Operation Manual* replaces the review figure on page 4.

Document Summary

Chapter	Description
Chapter 1: Setup	Contains a list of package contents and unpacking instructions.
Chapter 2: LS-475 Specifications	Contains operating environment specifications, as well as other physical details of the product.
Chapter 3: Operating Instructions	Provides instructions for setting the LS-475 to operate in Continuous and Pulsed Mode.

Product-Related Documentation

You can access documentation for Ocean Optics products by visiting our website at <http://www.oceanoptics.com>. Select *Technical* → *Operating Instructions*, then choose the appropriate document from the available drop-down lists. Or, use the **Search by Model Number** field at the bottom of the web page.

You can also access operating instructions for Ocean Optics products on the *Software and Technical Resources* CD included with the system.

Engineering-level documentation is located on our website at *Technical* → *Engineering Docs*.

Upgrades

Occasionally, you may find that you need Ocean Optics to make a change or an upgrade to your system. To facilitate these changes, you must first contact Customer Support and obtain a Return Merchandise Authorization (RMA) number. Please contact Ocean Optics for specific instructions when returning a product.

Chapter 1

Setup

Overview

The following sections provide instructions on unpacking and setting up your LS-475 Blue LED Pulsed Light Source.

Before using the LS-475 for the first time check for transport damage. Be sure to adhere to all warnings on the unit and in this manual.



Unpacking the LS-475

► Procedure

1. Unpack your lamp assembly carefully. Although the blue LED lamp is rigidly mounted, dropping this instrument can cause permanent damage.
2. Inspect the outside of the instrument and make sure that there is no damage. Do not use the instrument if damage is present. Contact your dealer for repair or replacement information, if necessary.
3. Use this instrument in a clean laboratory environment (see [Operating Environment](#)).

Contents

Your LS-475 package should contain the following:

- ❑ LS-475 Blue LED Pulsed Light Source
- ❑ One IC-DB15-2 interface cable for shutter operation

Additionally, you will need an approved power supply for the LS-475, such as the Mikropack PS-12V/1.25A power supply.

General Configuration

► Procedure

To set up your LS-475,

1. Plug the power supply into an outlet and into the back of the LS-475
2. Screw an optical fiber onto the SMA connector on the front of the light source.

Chapter 2

LS-475 Specifications

This section provides information on the operating environment and physical components of the LS-475.

Operating Environment

The following table provides information on optimizing the operating environment of your LS-475.

Operating Environment	The LS-475 Unit . . .
Moisture	Is designed for operation in dry rooms only.
Ventilation	Should be situated so that its location or position does not interfere with proper ventilation.
Heat	Should be situated away from any device that emits excessive heat.
Object and Liquid Entry	Should be positioned so that objects do not fall on top of the unit. Additionally, ensure that no liquids are spilled into the enclosure through openings.
Power Sources	Should be connected to an approved power supply, such as the Mikropack 12 VDC 1250mA analog regulated power supply (PS-12V/1.25A)

LS-475 Components

The following sections describe the components located on the front and rear of the LS-475 unit.

Front Panel



Fiber Optic Connector
– SMA 905 Compatible

Rear Panel



Power Input 12VDC

SUB-D 15 Pin
Connector


ON/OFF/TTL Switch

Pinout Information

The following table contains pinout information for the LS-475.

Pin	Description
1	na
2	na
3	na
4	na
5	na
6	na
7	na
8	na
9	na
10	Ground
11	na
12	na
13	TTL Signal – Shutter control
14	na
15	na
na = not applicable	

Pinout Diagram



Operating Instructions

Overview

The following sections provide instructions on operating the LS-475 Blue LED Pulsed Light Source.

Using the Continuous Mode

Continuous Mode means that the light coming from the LS-475 is continuous (not pulsed).

► *Procedure*

To set the LS-475 for Continuous Mode operation,

1. Move the switch on the back of the LS-475 to the ON position.
2. Move the switch to the OFF position to turn the lamp off.

Using the Pulsed Mode

The pulsing of the LS-475 is controlled through the Ocean Optics S2000 Spectrometer.

► *Procedure*

To set up the LS-475 for Pulsed Mode operation,

1. Plug one end of the supplied IC-DB15-2 accessory connector cable into the back of the LS-475 and the other end into the S2000 Spectrometer.
2. Move the switch on the back of the LS-475 to the TTL position. This places the light source in Pulsed Mode.

Enabling Pulse Mode on an S2000 Spectrometer

► Procedure

To enable Pulse Mode on the S2000 Spectrometer,

1. Remove your spectrometer from its housing. Do not tamper with the optical bench.

Note

If you have more than one channel in your system, you may have to disconnect the channels from one another. The master spectrometer is always on the bottom of a multiple channel system.

2. Locate jumper block 3 (JP3) in the center of the green circuit board. Jumper Block 3 consists of 10 pins labeled by rows (/16, /14, /12, /10 and 2). The configuration of these pins control the pulse frequency on the A/D converter connected to the S2000. The default factory setting is /16.
3. Configure the jumpers in JP3 for the desired pulse frequency.

Table 1 illustrates the various configurations of JP3 pins and their associated pulses per second.

Table 1: JP3 Configuration and Pulse Frequency

S2000 JP 3 Post #	DAQ 700 Frequency (Hz)	ADC500 / SAD500 Frequency (Hz)	ADC1000 Frequency (Hz)
/16	98.0	488.0	976.0
/14	24.0	122.0	244.0
/12	6.1	30.0	60.0
/10	1.5	7.6	15.2

For example, if you have an ADC1000 A/D converter, you have four choices for pulse frequency from the LS-475: 976, 244, 60 and 15. If you choose to configure 244 pulses per second, place a jumper over the pins next to the **/14** label.

When using the pulsed flash mode, you must ensure that the number of flashes is constant for every integration cycle. To achieve a constant number of flashes per integration cycle, the integration time must be a multiple of that shown in Table 2. Integration times are set in the OOIBase32 software. See the *OOIBase32 Spectrometer Operating Software, Operating Instructions* for more information.

Table 2: A/D Integration Time Specifications

S2000 JP3setting	Integration time for DAQ 700 Must be a multiple of:	Integration time for ADC500 / SAD500 Must be a multiple of:	Integration time for ADC1000 Must be a multiple of:
/16	512	128	64
/14	128	32	16
/12	32	8	4
/10	8 (with a min value of 24ms)	4	4

Index

A

A/D Integration Time Specifications, 9

C

components, 3
 front panel, 4
 rear panel, 4
Continuous Mode, 7

D

document
 audience, iii
 purpose, iii
 summary, iii

G

General Configuration, 2

J

JP3 Configuration and Pulse Frequency, 8

O

operating environment, 3
Operating Instructions, 7

P

package contents, 2
pinouts, 5
product-related documentation, iii
Pulse Mode
 S2000 Spectrometer, 8
Pulsed Mode, 7

S

S2000 Spectrometer
 Pulse Mode, 8
setup, 1
specifications, 3

U

unpacking procedure, 2
upgrades, iv

W

what's new, iii

