

MICROELECTRONIC INTERCONNECT MATERIALS

Mountain Ridge Business Park, Unit B12 1248 Sussex Turnpike, Randolph, New Jersey 07869-2908 Phone: 973.895-3600 Fax: 973.895-3617 www.koartan.com

Distributed in the UK, Ireland & Scandinavia by: Inseto, Tel: +44 (0)1264 334505 www.inseto.co.uk

REV. 103105

Technical Information

5680G Overglaze Paste

The 5680G is a high temperature overglaze designed for general protection of electronic circuitry. It fires at temperatures 750°C-900°C to a green shinny finish. The 5680G composition does not contain lead, cadmium, or highly toxic organic solvents. Key features include:

- RoHS Compliant
- Fully Vitreous
- Acid Resistant
- High Operating Temperatures.

TYPICAL FIRED FILM CHARACTERISTICS

Color Green Paste / Translucent Green Fired Film

Firing Temperature 750°C - 900°C

Surface Finish Shinny

COMPOSITION PROPERTIES

Viscosity: 130 ± 30 Kcps, when measured with Brookfield HBT, Spindle #14, utility cup, 10 rpm, 25°.

Specific Gravity: 1.5 – 1.9 g/cm³

Recommended Thinner: KOARTAN A-1039


RECOMMENDED PROCESSING PROCEDURE

Printing: Printing with 250 mesh stainless steel screen using 10-15 μ m emulsion and 45 degree angle is recommended. Other mesh counts, 200-325, and emulsion thicknesses, 5-25 μ m, may be used for special applications.

Coverage is approximately 150 cm² per layer, when utilizing 250 mesh screen and a wet print thickness of about 35 μ m.

Drying: Wet prints should be allowed to level for 5-10 minutes prior to drying. Dry for 10-15 minutes in a convection oven or belt dryer at 125°C-150°C.

Firing: Firing in air using a belt furnace and a 36-60 minute profile, with 10 minutes at a peak temperature of 750°C-900°C is recommended. Air flow rates must be optimized to ensure that the products of binder burn-off discharge properly and create a fully oxidizing atmosphere in the muffle.



Storage and Shelf Life: Store in tightly capped containers at room temperature. Shelf life is 6 months for unopened jars. Thorough mixing of the paste before each use is recommended. Under ordinary conditions of storage and use the product should not require thinning. However, solvent loss during extended printing runs may be replaced by incorporating up to 0.5% of Koartan A-1039 thinner.

The information presented herein is based on data believed to be dependable and is accurate and reliable to the best of our knowledge and belief, but not guaranteed to be so. Koartan Company assumes no liability arising from the use of this product or the information provided herein. Nothing herein is to be construed as recommending any practice or any product in violation of any patent or in violation of any law or regulation.